



Space-Saver Deactivator

The Sensormatic Essentials Space-Saver Deactivator is designed for convenient, simple deactivation in even the smallest checkstand areas. The antenna simply attaches around a single-plane vertical point-of-sale (POS) scanner to preserve precious counter space. The compact antenna conveniently deactivates AM EAS labels up to 12.7cm (5in) away from its surface, allowing cashiers to scan and deactivate protected merchandise in one simple motion. The optional Remote Alarm Module can be mounted almost anywhere on the checkstand to provide visual and audible confirmation when active labels are detected and deactivated. The locking key feature prevents unauthorized use of the deactivator when the POS is unattended.

When connected to a compatible EAS data management device, real-time deactivation counts can be generated into user-friendly customizable reports to provide business-critical data.

Retailer Values

- // Compact design and easy installation allows maximum use of checkout space
- // Single motion to scan and deactivate merchandise, improves throughput and productivity
- // Reliable deactivation for increased customer service and fewer nuisance alarms

Product Codes

ZBAMB1200T

AMB1220A Coil Antenna, Essentials Controller, Power Cord

Product Compatibility

All Sensormatic AM EAS Labels
Local Device Manager II (LDM II)
Deactivation Remote Alarm Module

Specifications

Depth	9.45cm (3.72in)
Width	20.3cm (7.98in)
Height	19.8cm (7.79in)
Weight	48kg (1.05lbs)
Coil Cable Length	1.83m (6ft)

Environmental Constraints

Operating Temperature
0°C to 40°C (32°F to 104°F)

Non-Operating Temperature
-40°C to 70°C (-40°F to 158°F)

Humidity
0 to 90%, non-condensing

CE This product is in conformity with RoHS II Directive 2011/65/EU and REACH Substances of Very High Concern as defined in Regulation (EC) No 1907/2006 and subsequent amendments to both.

